



Device 4inputs/outs KNX: Device 4inputs/outs KNX

01522.1

Device 4inputs/outs KNX

Device with 4 inputs/outputs, 4 NO relay outputs 16 A 250 V~, programmable with control function for lights, roller shutters with slat orientation, push buttons for local control, 4 programmable digital inputs for potential-free contacts, KNX standard, installation on DIN rail (60715 TH35), occupies 4 modules size 17.5 mm

Product Status

3 - Active

Minimum order quantity

1 NR

Sheets, Manuals, Documentation

- [Multilanguage instructions sheet \(928 kb\)](#)
- [Manuale installatore \(3360 kb\)](#)
- [Manuale installatore \(3307 kb\)](#)

Product Software

- [DB_ComponentiAutomazione_KNX_01.16_20210920.zip](#)
- [DB_ComponentiAutomazione_KNX_01.19_20230331.zip](#)




Drawings



Space view



Backside view



3D View

Technical data

- **Class group:** Installation bus systems
- **Class:** I/O device for bus system
- **Bus system KNX:** Yes
- **Bus system KNX-RF (Radio Frequent):** No
- **Bus system radio frequent:** No
- **Bus system LON:** No
- **Bus system Powernet:** No
- **Width in number of modular spacings:** 4
- **With bus connection:** Yes
- **LED controlling:** Yes
- **With LED indication:** Yes
- **Local operation/hand operation:** Yes
- **Suitable for C-load:** No
- **With switch function:** Yes
- **Rated current:** 16,00 A
- **External signal voltage necessary:** No
- **Different phases connectable:** Yes

Certifications

- 00. CE Marking - EU
- 27. KNX ([download](#))
- 43. UKCA mark - Great Britain
- 92. RoHS UAE
- 99. WEEE Directive ([download](#))

Packaging



Code 8007352644342
Quantity 1 NR
Dim. 11.7x10.8x7.1 [cm]
Weight 283 [g]

Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).