



## Supply unit 320mA KNX: Supply unit 320mA KNX

**01500.2**

### Supply unit 320mA KNX

Power supply unit for home automation with Bus output of 30 Vdc 320 mA, auxiliary output 30 V d.c., power supply 120-240 V~ 50/60 Hz, with decoupling coil, KNX standard, installation on DIN rail (60715 TH35) occupies 4 17,5 mm modules

### Product Status

3 - Active

### Minimum order quantity

1 NR


### Sheets, Manuals, Documentation

- [Multilanguage instructions sheet \(645 kb\)](#)

### Product Software

- [DB\\_ComponentImpianto\\_KNX\\_REL-01.11\\_20230915.zip](#)
- [DB\\_ComponentImpianto\\_KNX\\_REL-01.12\\_20231215.zip](#)


### Drawings



Space view



Backside view



3D View



### Technical data

- **Class group:** Installation bus systems
- **Class:** Power supply for bus system
- **Bus system KNX:** Yes
- **Bus system KNX-RF (Radio Frequent):** No
- **Bus system radio frequent:** Yes
- **Bus system LON:** No
- **Bus system Powernet:** No
- **Other bus systems:** None
- **Mounting method:** Other
- **Width in number of modular spacings:** 4
- **With LED indication:** Yes
- **Bus voltage stockable:** Yes
- **Number of lines to feed:** 2
- **Max. output current:** 320,00 mA

## Certifications

- 00. CE Marking - EU
- 27. KNX ([download](#))
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain
- 92. RoHS UAE
- 99. WEEE Directive ([download](#))

## Packaging



8 007352 550131

**Code** 8007352550131  
**Quantity** 1 NR  
**Dim.** 11.7x10.8x7.1 [cm]  
**Weight** 262.4 [g]

## Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).